



Xact Series Servo

Dynamic Integrated Performance

FrSky Electronic Co., Ltd.



	HV5101		HV5201 HV5202 HV5203			HV5301		HV5401 HV5402		HV5403
Photo/Style										
Weight (g)	18		23			41		72		72
Size (mm)	28*8*29		23*12*29			35*15*31		40*20*39		40*20*39
Torque (kgf.cm) ±15%@8.4V	6.8		4.2			6.1		8.7		26.2
Speed (S/60°) ±12%@8.4V	0.10		0.04			0.08		0.04		0.11

	HV5404 HV5405		HV5501 HV5502		HV5601 5611		HV5602 5612	
Photo/Style								
Weight (g)	72		58		9.5		9.5	
Size (mm)	40*20*39		41*20*27		23*8*19		23*8*19	
Torque (kgf.cm) ±15%@8.4V	32.0		19.3		4.1		4.1	
Speed (S/60°) ±12%@8.4V	0.13		0.11		0.05		0.05	

About F.Port 2.0:
Working with the F.Port 2.0 protocol, the telemetry data (like real-time current and voltage) of Xact servos can be achieved and transmitted back to the radio by connecting either F.Port 2.0 capable receiver or flight controller. All the preset servo options of speed and torque can be configured directly on an ACCESS radio through the host device of F.Port 2.0 line, and the configurable servo steering as well as travel degree are additions now can be expected on this series.

More information:

Features

- Digital High Resolution Magnetic Sensor*
- HV5611/5612: Potentiometer Sensor
- Full Metal Gears
- All Aluminum Housing by CNC
- Programmable by F.Port 2.0/Telemetry by F.Port 2.0
- Firmware Update
- 4.8-8.4V Supported
- Operating travel: 360°

*About the shell color, please refer to the actual product.

86-510-8518 7718
frsky@frsky-rc.com
www.frsky-rc.com
F-4, Building C, Zhongxiu Technology Park, No.3
Yuanxi Road, Wuxi, 214125, Jiangsu, China